



Tools Required:

- Phillips-head screwdriver medium
- Flat-head screwdriver medium



Dimensions


- A:** 1-1/2"
- B:** 7-1/4"
- C:** 2-1/2"



Notice to Installer for 19 545:

1. Bega custom wiring boxes are intended for use with Bega luminaires that can not be installed over standard wiring boxes. Please note dimensions for opening size required for proper installation
2. Do not pump concrete directly on top of the wiring box. Use care in placing concrete around the wiring box to avoid dislodging it from the form.
3. In conformance with UL Standard 1598, a silicone based sealant must be used between the luminaire and supporting wall (exterior use).
4. Refer to luminaire installation instructions for wiring box installation orientation.

Figure 1



19 545 - Installation:

1. Attach wiring box to framing of wall or suitable backing, using hardware (by others).
2. Make conduit connections to the wiring box and pull individual supply conductors as required.
3. Wiring box must be installed flush with the finished wall surface.
4. Before finishing the wall, route wiring out of the opening in the wiring box to facilitate making wiring connections to the luminaire.
5. Refer to luminaire installation instructions to complete installation.

19 545

Relamping/Maintenance

Clean luminaire regularly with solvent-free cleansers from dirt and debris. Do not use high pressure cleaners.

Accessories

Please refer to the appropriate accessory installation sheet for further instruction when applicable.

Replacement Parts

Description

Part No

In the interest of product improvement, BEGA reserves the right to make technical changes without notice.

Product Safety Warnings:

THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR WET LOCATIONS.

MIN 90°C SUPPLY CONDUCTORS.

CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS. CONVIENT AUX EMPLACEMENTS MOUILLÉS.

LES FILS D'ALIMENTATION 90°C MIN.
