


**Tools Required:**

3mm hex key  
Philips medium screwdriver



**Dimensions**

A: 10-1/4 "

B: 10-1/4 "

C: 3-1/2 "



**Weight:** 8.81 lbs.


**Notice to Installer for 33 233:**

1. **BEGA luminaires may be damaged if connected to conduit systems containing water - Article 300-5G of National Electric Code requires that "Conduits or raceways through which moisture may contact energized live parts shall be sealed or plugged at either or both ends".**
2. Mounts directly to standard recessed 4" octagonal wiring box (by others) using BEGA provided mounting kit.
3. In conformance with U.L. Standards 1958, a silicone-based sealant **MUST** be used between the luminaire and mounting surface.
4. **WARNING:** LEDs are high-quality electronic components! Please avoid touching the LED module(s) during installation.

**33 233 - Installation:**

1. Loosen set screw on side of luminaire housing. Open luminaire hinged cover.
2. Feed luminaire wires through fixture base, IP nipple, and center hole in mounting strap.
3. Make supply wiring and luminaire wiring connections and tuck in to the octagonal wiring box:  
MAIN VOLTAGE SUPPLY WIRE TO BLACK LUMINAIRE WIRE  
NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LUMINAIRE WIRE  
GREEN GROUND WIRE TO GREEN LUMINAIRE WIRE
4. Attach mounting strap (provided) to wiring box using outlet box screws (by others).
5. Attach 1/4" nipple to mounting strap (provided) and place luminaire over nipple.  
NOTE: Place a small bead of silicone around the back side of the luminaire base that will come in contact with the finished wall (exterior applications only).
6. Attach the luminaire base to the adaptor plate over a 4" standard octagonal wiring box using provided acorn nuts (See figure for mounting hole spacing).  
NOTE position of orientation arrow on luminaire base and install accordingly.
7. Use lockwasher and nut (provided) to secure luminaire on nipple. Tighten screw.
8. Replace luminaire cover back on to the luminaire housing. Secure with set screws.

**Figure 1**



**Relamping/Maintenance**

Loosen set screw on side of luminaire housing. Remove lens from luminaire base. Clean glass and luminaire using only solvent-free cleansers. Replace lens and tighten set screw.

**Accessories**

Please refer to the appropriate accessory installation sheet for further instruction when applicable.

**Replacement Parts**

Description	Part No
Lens	11286111
LED Driver	75983-02
LED Module (3000K)	LED-0841/930
LED Module (4000K)	LED-0841/940

**Lamp:** 11.5W LED

**Product Safety Warnings:**

**THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR WET LOCATIONS.**

**MIN 90°C SUPPLY CONDUCTORS.**

**CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS. CONVIENT AUX EMPLACEMENTS MOUILLÉS.**

**LES FILS D'ALIMENTATION 90°C MIN.**

---