

Tools Required:

- 5mm hex key
- Adjustable wrench



- Dimensions**
- A: 39-3/8 "
 - B: 4-1/2 "
 - C: 2-1/4 "



Weight: 12.1 lbs.


Notice to Installer for 84 380:

- 1. See page 2 for specific product safety warnings.
- 2. Integral LED module and driver provided by BEGA within luminaire housing.
- 3. Leader cable must be secured to a wet location rated junction box with UL Listed or CSA Certified liquid tight cord grip suitable for flexible leader cable provided.
- 4. Outer diameter of the 5-wire 77 284 leader cable: 0.35" - 0.38".

84 380 - installation:

- 1. Loosen (2) 5mm captive hex screws and detach mounting base from the luminaire
- 2. Attach the base to a finished mounting surface with (2) screws and washers (by others)
- 3. Adjust aiming, if desired, by removing (2) hex nuts and washers to detach mounting base from mounting plate.
- 4. Move mounting base on ribbed track of mounting plate to desired aiming location
- 5. Reattach mounting base to the mounting plate with hex nuts.
- 6. Remove end cap from 5-pin connector and connect luminaire cables to the leader and/or jumper cables. Leave endcap on 5-pin connector if not attached to either a leader or jumper cable.
- 7. Directly connected cables through openings on either end of mounting base and replace luminaire. Tighten (2) hex screws to secure.
- 8. Make leader cable wiring connections in wet location wiring box (by others):
MAIN VOLTAGE SUPPLY WIRE TO BLACK LEADER WIRE
NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LEADER WIRE
GREEN GROUND WIRE TO GREEN LEADER WIRE
Dimming (if applicable):
DIMMING CONTROL WIRE (+) TO POSITIVE LEADER DIM WIRE
DIMMING CONTROL WIRE (-) TO NEGATIVE LEADER DIM WIRE

Figure 1:



Relamping/Maintenance

Clean luminaire regularly with solvent-free cleansers from dirt and debris. Do not use high pressure cleaners.

Lamp: 25.6W LED

Accessories

Please refer to the appropriate accessory installation sheet for further instruction when applicable.

| | |
|-------------------------|-------------|
| Leader cable | 77 284 |
| End-to-end jumper cable | 77 285- ETE |
| 1ft jumper cable | 77 285-1 |
| 3ft jumper cable | 77 285-3 |
| 5ft jumper cable | 77 285-5 |
| 10ft jumper cable | 77 285-10 |

Replacement Parts

| Description | Part No |
|----------------------------|------------------|
| LED Driver (120-277V) | (X1)76135-01 |
| LED Module (Tunable White) | (X2)LED-0928/8TW |

In the interest of product improvement, BEGA reserves the right to make technical changes without notice.

Product Safety Warnings:

THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR WET LOCATIONS.

MIN 60°C SUPPLY CONDUCTORS.

CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS. CONVIENT AUX EMPLACEMENTS MOUILLÉS.

LES FILS D'ALIMENTATION 60°C MIN.