

Tools Required:

- 4mm hex key
- Drill

Protection Class: IP 65

Weight: 7.7 lbs



Dimensions
A: 5-1/2"
B: 26"



- Notice to Installer for 99 620:**
- See page 2 for specific product safety warnings.
 - Fixture may be damaged if connected to conduit systems that contain water - Article 300-5G of the National Electric Code requires that "Conduits or raceways through which moisture may contact energized live parts shall be sealed or plugged at either or both ends."
 - For proper installation, an accompanying bollard head must be selected with the bollard tube.
 - 79 824 anchorage kit (included) must be installed in concrete pad/foundation.
 - It is recommended that when installing in planting areas the bollard base be slightly elevated to avoid prolonged submerging during heavy rains.
 - Wet location listing does not imply suitability for exposure to standing water for long periods of time.
 - LEDs are high-quality electronic components! Please avoid touching the light output opening of the LED directly during installation.

- 79 824 anchorage installation:**
- Provide means to bring supply wiring to the bollard in accordance with local code and pour concrete for finished grade. The bollard base has a 1 3/4" conduit hole for conduit entry.
 - Loosen set screw at bollard base and remove base plate.
 - After establishing finished grade, mark the location of the (3) anchorage drill holes using the bollard base of the fixture as a template.
 - Drill (3) 1/4" holes in concrete at the marked locations.
 - Feed supply wires up through bollard base and conduit.
 - Align bollard base holes with drill holes.
 - Drive the sleeve anchors through the bollard base and into the drilled holes until seated flush.

- 99 620 installation:**
- Remove (3) hex bolts and washers, once anchorage is set.
 - Leave template in place to provide a smooth, flat surface to mount the base.
 - Turn the base plate and remove from bollard, after loosening the 4mm set screw.
 - Align base plate holes with anchorage holes.
 - Bolt the base plate to the anchorage kit using the (3) hex bolts and washers.
 - Bring supply wiring into internal wiring box (provided) for connections to be made to the female 5-pin connector.
MAIN VOLTAGE SUPPLY WIRE TO BLACK 5-PIN CONNECTOR WIRE;
NEUTRAL (COMMON) SUPPLY WIRE TO WHITE 5-PIN CONNECTOR WIRE;
GREEN GROUND WIRE TO GREEN 5-PIN CONNECTOR WIRE.
 - Dimming (if applicable):
DIMMING CONTROL WIRE (+) TO POSITIVE 5-PIN CONNECTOR
DIM CONTROL WIRE
DIMMING CONTROL WIRE (-) TO NEGATIVE 5-PIN CONNECTOR
DIM CONTROL WIRE
 - Place the bollard over the base plate so that the (3) notches in the base plate align with the top.
 - Secure the bollard by tightening the 4mm set screw at the base.
 - Install bollard head per bollard head installation instructions.




Figure 1: Bollard Base Detail

Relamping/Maintenance	Accessories	Replacement Parts	
		Description	Part No
	Please refer to the appropriate accessory installation sheet for further instruction when applicable.		
	Anchorage Kit - Included		79 824
	Direct Burial Anchorage		70 894

In the interest of product improvement, BEGA reserves the right to make technical changes without notice.

Product Safety Warnings:

THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR WET LOCATIONS.

MIN 90°C SUPPLY CONDUCTORS.

CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS. CONVIENT AUX EMPLACEMENTS MOUILLÉS.

LES FILS D'ALIMENTATION 90°C MIN.
