


Tools Required:

- Medium flathead screwdriver
- Medium Phillips-head screwdriver
- 3mm hex head screw driver

Overview:

LED Watts: 25.2W
System Watts: 28.0W
Controllability: Triac, ELV, 0-10V dimmable
Weight: 11.2 lbs.



Dimensions

A: 18-1/8"
B: 3-7/8"
C: 11"




Notice to Installer:

1. See page 2 for specific product safety warnings.
2. Mounts directly to ceiling or wall over recessed standard 4" octagonal junction box (by others)
3. LEDs are high-quality electronic components! Please avoid touching LED directly during installation.

Installation:

1. Remove opal glass from luminaire housing by turning glass component counterclockwise, until it stops. Once glass stops, remove it from housing
2. Carefully undo (4) 3mm hex head screws on LED board. Set LED board aside.
3. Make supply wiring and luminaire wiring connections inside the recessed junction box:
MAIN VOLTAGE SUPPLY WIRE TO BLACK LUMINAIRE WIRE
NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LUMINAIRE WIRE
GREEN GROUND WIRE TO GREEN LUMINAIRE WIRE
- Dimming (if applicable):
DIMMING CONTROL WIRE (+) TO POSITIVE PURPLE DRIVER DIM CONTROL WIRE
DIMMING CONTROL WIRE (-) TO NEGATIVE GREY DRIVER DIM CONTROL WIRE
4. Mount luminaire housing directly to ceiling or wall over recessed junction box using mounting holes (Figure 1).
5. Reconnect LED board using quick connect, and reattach to housing using (4) 3mm hex head screws making sure not to overtighten.
6. Replace opal glass by twist-lock closure, turning the class clockwise until it is locked. Assure snug fit against housing.



Accessories

Please refer to the appropriate accessory installation sheet for further instruction when applicable.

Maintenance:

Clean regularly with solvent-free cleaner removing dirt and debris. Do not use high pressure cleaners.

Replacement Parts

See label inside of fixture for LED replacement part number.
Consult factory for all other replacement components.

Product Safety Warnings:

THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR DAMP LOCATIONS. MIN 90°C SUPPLY CONDUCTORS.

CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS. CONVIENT AUX EMPLACEMENTS HUMIDE.

LES FILS D'ALIMENTATION 90°C MIN.