


Tools Required:

- Medium flathead screwdriver
- Medium Phillips-head screwdriver
- 2.5mm hex head screw driver



Dimensions

A: 10-1/4"

B: 3-1/8"



Overview:


LED Watts: 15.2W
 System Watts: 19.0W
 Controllability: 0-10V dimmable
 Weight: 6.4 lbs.



Notice to Installer:

1. See page 2 for specific product safety warnings.
2. Select the desired housing material finish by using appropriate code number as suffix.
 Code number .1 - White
 Code number .2 - Stainless steel
 Code number .3 - Chrome
3. Mounts directly to ceiling or wall over recessed standard 4" octagonal junction box (by others)
4. LEDs are high-quality electronic components! Please avoid touching LED directly during installation.

Figure 1:



Installation:

1. Remove trim and lens from luminaire housing by twisting outer trim counter clockwise and set aside.
2. Carefully undo (4) 2.5mm hex head screws on LED board. Disconnect quick connect, and set LED board aside.
3. Make supply wiring and luminaire wiring connections inside the recessed junction box:
 MAIN VOLTAGE SUPPLY WIRE TO BLACK LUMINAIRE WIRE
 NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LUMINAIRE WIRE
 GREEN GROUND WIRE TO GREEN LUMINAIRE WIRE
 Dimming (if applicable):
 DIMMING CONTROL WIRE (+) TO POSITIVE PURPLE DRIVER DIM CONTROL WIRE
 DIMMING CONTROL WIRE (-) TO NEGATIVE GREY DRIVER DIM CONTROL WIRE
4. Mount luminaire housing directly to ceiling or wall over recessed junction box using mounting holes (Figure 1).
5. Reconnect LED board using quick connect, and reattach to housing using (4) 2.5mm hex head screws making sure not to overtighten.
6. Replace luminaire trim and lens by twisting back on to luminaire housing in clockwise rotation making sure the gasket is seated properly.

Accessories

Please refer to the appropriate accessory installation sheet for further instruction when applicable.

Maintenance:

Clean regularly with solvent-free cleaner removing dirt and debris. Do not use high pressure cleaners.

Replacement Parts

See label inside of fixture for LED replacement part number.

Consult factory for all other replacement components.

Product Safety Warnings:

THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR DAMP LOCATIONS. MIN 90°C SUPPLY CONDUCTORS.

CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS. CONVIENT AUX EMPLACEMENTS HUMIDE.

LES FILS D'ALIMENTATION 90°C MIN.