


Tools Required:

- 5/16" wrench
- Medium Phillips screwdriver



- **Dimensions**
- B
- A
- A: 4 7/8"
- B: 4 5/8"



Overview:

System Watts: 4.8 W
 LED Watts: 6.4 W
 Controllability: 0-10V dimmable
 Weight: 2.7 lbs.
 Protection Class: IP65


Notice to Installer:

1. **BEGA luminaires may be damaged if connected to conduit systems containing water- Article 300-5G of National Electric Code requires that "Conduits or raceways through which moisture may contact energized live parts shall be sealed or plugged at either or both ends".**
2. Mounts directly to a standard octagonal 4" wiring box (by others) using mounting plate (supplied).
3. In conformance with U.L. Standards 1598, a silicone-based sealant **MUST** be used between the mounting plate edge and supporting wall.
4. LEDs are high-quality electronic components! Please avoid touching the light output opening of the LED directly during installation.

Installation:

1. Twist lens counter-clockwise and remove lens from fixture.
 2. Install (2) long 8-32 x 3/4" mounting screws (provided) in the back of the mounting plate as shown.
 3. Attach mounting plate to wiring box using (2) 8-32 x 1/2" screws provided. Feed luminaire wires through luminaire base and mounting plate.
 4. Make supply wiring and luminaire wiring connections inside the wiring box:
 CONNECT WHITE (common) SUPPLY WIRE TO WHITE FIXTURE LEAD
 CONNECT BLACK (hot) SUPPLY WIRE TO BLACK FIXTURE LEAD
 CONNECT GREEN (ground) SUPPLY WIRE TO GREEN FIXTURE LEAD
- 0-10V Dimming (if applicable):**
 DIMMING CONTROL WIRE (+) TO POSITIVE DRIVER DIM CONTROL WIRE
 DIMMING CONTROL WIRE (-) TO NEGATIVE DRIVER DIM CONTROL WIRE
5. Place a small bead of silicone around the back side of the luminaire base that will come in contact with the finished wall.
 6. Attach luminaire to mounting plate over the mounting screws using the (2) 8-32 hex nuts provided. Tighten the nuts to back the screws into the wiring box and secure the plate to the box.
 7. Screw lens onto housing carefully, making sure the gasket is sealed properly.

Figure 1: Generic Image



Accessories

Please refer to the appropriate accessory installation sheet for further instruction when applicable.

Maintenance:

Clean regularly with solvent-free cleaner removing dirt and debris. Do not use high pressure cleaners.

Replacement Parts

See label inside of fixture for LED replacement part number.

Consult factory for all other replacement components.

Product Safety Warnings:

THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR WET LOCATIONS.

MIN 90°C SUPPLY CONDUCTORS.

CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS. CONVIENT AUX EMPLACEMENTS MOUILLÉS.

LES FILS D'ALIMENTATION 90°C MIN.