


Tools Required:

- 4mm hex key
- Flat head screw driver medium
- Phillips head screw driver medium



Dimensions

- A: 8-1/2 "
- B: 4-3/8 "
- C: 4 "




Protection Class: IP65
Weight: 3.1 lbs

Notice to Installer for 22 363:

- For wall applications only.
- Mounts directly to wall over standard recessed 4" wiring box (by others).
- In conformance with UL Standard 1598, a silicone based sealant must be used between luminaire and supporting wall.
- LEDs are high-quality electronic components! Please avoid touching the light output opening of the LED directly during installation.

22 363 - installation:

- Loosen (2) 4mm hex screws on faceplate and remove cover.
- Make supply wiring and luminaire wiring connections inside the wiring box:
CONNECT WHITE (common) SUPPLY WIRE TO WHITE FIXTURE LEAD
CONNECT BLACK (hot) SUPPLY WIRE TO BLACK FIXTURE LEAD
CONNECT GREEN (ground) SUPPLY WIRE TO GREEN FIXTURE LEAD
- Dimming (if applicable):
DIMMING CONTROL WIRE (+) TO POSITIVE DRIVER DIM CONTROL WIRE
DIMMING CONTROL WIRE (-) TO NEGATIVE DRIVER DIM CONTROL WIRE
- Place a small bead of silicone around the back side of the luminaire base that will come in contact with the finished wall (exterior applications only).
- Mount luminaire to wall over recessed wiring box using hardware by others (minimum size 8-32 screws).
- Replace cover and tighten (2) hex screws



Relamping/Maintenance
No relamping required.

Lamp: 7.7W LED Module

Accessories
Please refer to the appropriate accessory installation sheet for further instruction when applicable.

Replacement Parts	
Description	Part No
Face Plate	FP2363
Driver (120-277V)	75943
LED Module (3000K)	LED-0269/830
LED Module (4000K)	LED-0269/840

In the interest of product improvement, BEGA reserves the right to make technical changes without notice.

Product Safety Warnings:

THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR WET LOCATIONS.

MIN 90°C SUPPLY CONDUCTORS.

CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS. CONVIENT AUX EMPLACEMENTS MOUILLÉS.

LES FILS D'ALIMENTATION 90°C MIN.
