


Tools Required:

- 4mm hex key
- Flat head screw driver medium
- Phillips head screw driver medium



Dimensions

- A: 12-1/2 "
- B: 4-3/8 "
- C: 4 "




Protection Class: IP65  
Weight: 4.2 lbs

Notice to Installer for 22 365:

- See page 2 for specific product safety warnings.
- For wall applications only.
- Mounts directly to wall over standard recessed 4" wiring box (by others).
- In conformance with UL Standard 1598, a silicone based sealant must be used between luminaire and supporting wall.
- LEDs are high-quality electronic components! Please avoid touching the light output opening of the LED directly during installation.

22 365 - Installation:

- Loosen (2) 4mm hex screws on faceplate and remove cover.
- Make supply wiring and luminaire wiring connections inside the wiring box:  
CONNECT WHITE (common) SUPPLY WIRE TO WHITE FIXTURE LEAD  
CONNECT BLACK (hot) SUPPLY WIRE TO BLACK FIXTURE LEAD  
CONNECT GREEN (ground) SUPPLY WIRE TO GREEN FIXTURE LEAD  
Dimming (if applicable):  
DIMMING CONTROL WIRE (+) TO POSITIVE DRIVER DIM CONTROL WIRE  
DIMMING CONTROL WIRE (-) TO NEGATIVE DRIVER DIM CONTROL WIRE
- Place a small bead of silicone around the back side of the luminaire base that will come in contact with the finished wall (exterior applications only).
- Mount luminaire to wall over recessed wiring box using hardware by others (minimum size 8-32 screws).
- Replace cover and tighten (2) hex screws



MOUNTING DETAIL

Relamping/Maintenance  
No relamping required.

Accessories  
Please refer to the appropriate accessory installation sheet for further instruction when applicable.

Replacement Parts	
Description	Part No
Face Plate	FP2365
Driver (120-277V)	76061
LED (3000K)	LED-0269/830
LED (4000K)	LED-0269/840

Lamp: 15.4W LED Module

In the interest of product improvement, BEGA reserves the right to make technical changes without notice.

---

**Product Safety Warnings:**

**THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR WET LOCATIONS.**

**MIN 90°C SUPPLY CONDUCTORS.**

**CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS. CONVIENT AUX EMPLACEMENTS MOUILLÉS.**

**LES FILS D'ALIMENTATION 90°C MIN.**

---