



Tools Required:

- 3mm hex key
- 4mm hex key
- 11/32" Nut driver
- Phillips medium screwdriver



Dimensions

- A: 10-1/4 "
- B: 3 "
- C: 6 "



Protection Class: IP65

Weight: 3.6 lbs.

Notice to Installer for 33 361:

- See page 2 for specific product safety warnings.
- Mounts directly to finished surface over standard recessed single gang box (by others)
- In conformance with UL Standard 1598, a silicone based sealant must be used between luminaire and supporting wall.
- Integral LED module and LED driver supplied by BEGA.

33 361 - installation:

- Loosen set screw at luminaire canopy and remove luminaire mounting plate.
- Feed luminaire wires through luminaire base.
- Make supply wiring and luminaire wiring connections in the octagonal wiring box:
MAIN VOLTAGE SUPPLY WIRE TO BLACK LUMINAIRE WIRE
NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LUMINAIRE WIRE
GREEN GROUND WIRE TO GREEN LUMINAIRE WIRE
Dimming (if applicable):
DIMMING CONTROL WIRE (+) TO POSITIVE DRIVER WIRE
DIMMING CONTROL WIRE (-) TO NEGATIVE DRIVER WIRE
- Place a small bead of silicone around the back side of the mounting base and luminaire that will come in contact with the finished wall (exterior applications only).
- Mount mounting plate to wall over standard recessed single gang box using hardware by others.
- Mount luminaire to mounting plate and tighten set screw to secure luminaire.

Relamping/Maintenance	Accessories	Replacement Parts	
No relamping necessary.	Please refer to the appropriate accessory installation sheet for further instruction when applicable.	Description	Part No
		Lens	141119
		LED driver (120-277V)	75940
		LED Module 3000K	LED-0590/930
		LED Module 4000K	LED-0590/940
Lamp:	16.5W LED		

Product Safety Warnings:

THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR WET LOCATIONS.

MIN 60°C SUPPLY CONDUCTORS.

CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS. CONVIENT AUX EMPLACEMENTS MOUILLÉS.

LES FILS D'ALIMENTATION 60°C MIN.