


Tools Required:

- 2.5mm hex key
- Flat head screw driver medium



- Dimensions**
- A: 9-7/8 "
  - B: 4-3/8 "
  - C: 3 "



Weight: 4.4 lbs

Notice to Installer for 50 146:

- See page 2 for specific product safety warnings.
- Select the desired trim ring or housing material finish by using appropriate code number as suffix.
  - 50 146.1 - White
  - 50 146.2 - Stainless steel
  - 50 146.3 - Chrome
- Mounts directly to wall over standard recessed single-gang junction box (by others).


50 146 - installation:

- Remove faceplate from base of luminaire by unscrewing (2) 2.5mm set screws.
- Feed luminaire wires through base of the luminaire.
- Make supply wiring and luminaire wiring connections inside the wiring box:
  - MAIN VOLTAGE SUPPLY WIRE TO BLACK LUMINAIRE WIRE
  - NEUTRAL (COMMON) SUPPLY WIRE TO WHITE LUMINAIRE WIRE
  - GREEN GROUND WIRE TO GREEN LUMINAIRE WIRE

Dimming (if applicable):

- DIMMING CONTROL WIRE (+) TO POSITIVE DRIVER DIM CONTROL WIRE
  - DIMMING CONTROL WIRE (-) TO NEGATIVE DRIVER DIM CONTROL WIRE
- Mount luminaire base directly to wall over recessed single-gang junction box using hardware (by others)
  - Replace faceplate by evenly tightening (2) set screws.

Figure 1



Relamping/Maintenance

Unscrew glass by turning counter-clockwise. Clean glass and luminaire using on solvent-free cleansers. Replace glass .

Accessories

Please refer to the appropriate accessory installation sheet for further instruction when applicable.

Replacement Parts

Description	Part No
Driver (120-277V)	76049
LED Module (3000K)	LED-0696/830
LED Module (4000K)	LED-0696/840

Lamp: 25.2W LED Module

**Product Safety Warnings:**

**THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED. SUITABLE FOR DAMP LOCATIONS.**

**MIN 90°C SUPPLY CONDUCTORS.**

**CE PRODUIT DOIT ÊTRE INSTALLÉ SELON LE CODE D'INSTALLATION PERTINENT, PAR UNE PERSONNE QUI CONNAÎT BIEN LE PRODUIT ET SON FONCTIONNEMENT AINSI QUE LES RISQUES INHÉRENTS. CONVIENT AUX EMPLACEMENTS HUMIDES.**

**LES FILS D'ALIMENTATION 90°C MIN.**

---